

Total No. of Questions—12]

[Total No. of Printed Pages—4+2

Seat No.	
-------------	--

[4757]-117

S.E. (Mech/Automobile) (Second Semester) EXAMINATION, 2015

IC ENGINE

(2008 PATTERN)

Time : Three Hours

Maximum Marks : 100

N.B. :— (i) Answer *three* questions from each Section.

(ii) Answers to the two Sections should be written in separate answer-books.

(iii) Neat diagrams must be drawn wherever necessary.

(iv) Use of logarithmic tables, slide rules, Mollier charts, electronic pocket calculator and steam tables is allowed.

(v) Assume suitable data, if necessary.

SECTION I

1. (a) Compare Otto and Dual cycle for : [8]

(i) Constant maximum pressure and same heat input

(ii) Same compression ration and same heat input.

(b) In an ideal diesel cycle, the pressure and temperature are 1.03 bar and 27°C respectively. The maximum pressure in the cycle

P.T.O.

is 47 bar and the heat supplied during cycle is 545 kJ/kg.

Determine :

- (i) Compression ration.
- (ii) The temperature at the end of compression.
- (iii) The temperature at the end of constant pressure combustion
- (iv) Air standard efficiency.

Assume $r = 1.4$, $C_p = 1.004$ J/kg-K for air [10]

Or

- 2. (a) Explain in brief how chemical equilibrium affects the performance of the engine. [6]
 - (b) Draw theoretical and actual valve timing diagram for four stroke petrol engine. Explain the reason for difference. [6]
 - (c) Explain pumping and friction losses and their effects on the power output of the engine. [6]
-
- 3. (a) Explain the phenomenon of pre-ignition. How pre-ignition leads to detonation and vice-versa ? Explain how pre-ignition can be detected. [8]

(b) Explain with neat sketch the following system of carburetor : [8]

(i) Idling system

(ii) Chock

Or

4. (a) Explain any *two* types of combustion chamber used in SI engines. [8]

(b) What are advantages and disadvantages of petrol injection system over conventional carburetor system. [4]

(c) Explain why rich mixture is required for : [4]

(i) Idling

(ii) Sudden acceleration.

5. (a) What are functional requirement of injection system ? [8]

(b) Explain with sketch the following type of injection system :

(i) Common rail system.

(ii) Unit injection system. [8]

Or

6. (a) Explain stage of combustion in CI engine. [8]

- (b) Write short notes on the following : [8]
- (i) Supercharging
 - (ii) Turbo charging.

SECTION II

7. (a) What are basic requirements of ideal ignition system ? [4]
- (b) What are main functions of lubricating system ? Explain dry sump lubrication system. [8]
- (c) Write short note on additives used in lubricating system. [4]

Or

8. (a) Define intake manifold and their functions. State material used. Discuss the requirement for design of intake manifold. [8]
- (b) Explain working of spring loaded mechanical governor with the help of neat sketch used for diesel engine. [8]
9. (a) What is dynamometer ? Name various type of dynamometer. Explain Prony type of dynamometer with the help of neat sketch. [10]
- (b) Write short notes on : [8]
- (i) Heat balance sheet
 - (ii) Various factors affecting volumetric efficiency.

Or

10. (a) A six cylinder gasoline engine operate on four stroke cycle. The bore of each cylinder is 80 mm and stroke 100 mm. The clearance volume per cylinder is 70 CC. At a speed of 4000 r.p.m., the fuel consumption is 30 kg/hr and the torque developed is 150 Nm.

Calculate :

- (i) The brake power
- (ii) The brake mean effective pressure
- (iii) The brake mean thermal efficiency.

Assume CV of fuel = 43,000 kJ/kg.

Also estimate relative efficiency when engine works on constant volume cycle with $\gamma = 1.4$ for air. [12]

- (b) Compare battery ignition and magneto-ignition system. [6]
11. (a) Enlist the specification of an automobile engine. [6]
- (b) Discuss various types of exhaust emission from automobile. Which of these are harmful ? [6]
- (c) Mention the modification required if hydrogen is used in SI engine as a substitute fuel. [4]

Or

12. Write short notes on :

[16]

- (i) MPFI
- (ii) DTSi
- (iii) Bharat Norms
- (iv) Fuel-Air Equivalence ration.